

SPERRY MARINE UK
Service Bulletin No. 39

Product: Decca BridgeMaster I & II Series Radars

Subject: Software Compatibility Chart

PROCESSOR PCB			OPTIONS PCB					
DISPLAY			AUTOTRACK			GEOGRAPHICS		
VERSION	U54	U68	VERSION	U66	U72	VERSION	U86	U94
V1.0	3012D002	3012D003						
V2.0	3012D008	3012D009						
V3.0	3012D010	3012D011						
V4.0	3012D016	3012D017	V1.0	3012D004	3012D005			
V5.0	3013D002	3013D003	V2.0	3012D018	3012D019	V1.0	3012D006	3012D007
V6.0	3013D012	3013D013	V3.0	3012D020	3012D021	V2.0	3012D022	3012D023
V6.1	3013D016	3013D017	V4.0	3012D030	3012D031	V3.0	3012D026	3012D027
V6.2	3013D022	3013D023						
V6.5	3013D040	3013D041						
V6.6	3013D054	3013D055						
V7.0	3013D030	3013D031	V7.0	3012D036	3012D037	V7.0	3012D038	3012D039
V7.1	3013D036	3013D037	V7.1	3012D044	3012D045			
V7.4	3013D052	3013D053	V7.2	3012D054	3012D055			
V8.0	3013D048	3013D049	V8.0	3012D056	3012D057	V8.0	3012D058	3012D059
V8.1	3013D058	3013D059						
V8.4	3013D066	3013D067						
V8.6	3013D070	3013D071						
V8.7	3013D210	3013D211						

VALID COMBINATION: WITHIN HEAVY BOXES ONLY e.g. Display6.5/Autotrack3.0/Geographics3.0

Notes:

1. V1.0 & V2.0 for information only. No longer used (see DV1& DV5)
2. With a Basic Display any version will work in any Processor PCB. U61 can be either 31GAA007 or 31 GAA041
3. With Autotrack/Geographics Options and Display V5.0 or greater U61 must be 31GAA041
4. V7.0 or greater is BMII